

New 2023 Edition 2>Wall & Ceiling LED

12120F/W/W



20W COB LED cylinder.

Complete with 450mA driver.

Interchangeable reflector rings can be ordered separately.


Complies with standard EN60598-1 and any other specific standards.



Downloads



Dimensions



Accessories



050300B/BS



050300B/W



050300BH/B



0750B/15



0750B/24

Physical Specification

Item Group

New 2023 Edition 2

Family

Wall & Ceiling LED

Order Code

12120F/W/W

Colour

White

Material


Die Cast

Shape

Circular


| | |
|-----------------|-------|
| Height | 100mm |
| Diameter | 100mm |
| Surface Ceiling | Yes |
| Indoor | Yes |
| Adjustable | No |

Electrical Characteristics


| | |
|------------------|---|
| Gear | Built In |
| Fitting + Driver | |
| Input Voltage | 220-240V |
| 50 Hz | Yes |
| 60 Hz | Yes |
| Safety Class |  |
| Power(Watts) | 20W |
| IP Rating | IP20 |
| Light Source | LED built in |
| Dimmable | No |

| | |
|---------------|------------------|
| Fitting | |
| Input Type | Constant Current |
| Input Current | 450mA |
| Voltage | 40V |
| Power(Watts) | 18W |
| IP Rating | IP20 |
| Light Source | LED built in |
| LED Type | COB |
| LED Brand | Bridgelux |
| LED Number | 1 |

| | |
|------|--|
| Gear | |
|------|--|

| | |
|------------------|---|
| Gear Type | Led Driver |
| Input Voltage | 220-240V |
| 50 Hz | Yes |
| 60 Hz | Yes |
| Power(Watts) | 12,15-18,9W |
| Power Factor | 0,9 |
| Constant Current | Yes |
| 450mA | 27-42V |
| IP Rating | IP20 |
| Safety Class |  |
| Dimmable | No |
| Housing Material | Plastic |
| Output Terminal | Connector |
| Brand | KEGU |

Illumination Data

| | |
|----------------------|---|
| Colour Temperature | 3000K |
| Lumen Output | 2400lm |
| Light Efficiency | 120lm/W |
| CRI | 90 |
| Beam Angle | 38° |
| Illumination Diagram |  |
| Dark Light | Yes |

Packing Info

| | |
|------------|---------------|
| Box Weight | 0.660kg |
| Pcs/Carton | 10 |
| Barcode | 5291889076599 |
| HS Code | 9405413990 |

Warranty

5 years

switch to
one light!

one
LIGHT

